



## Full Reset HP OfficeJet 6700 All-in-one Printer

For those wanting to perform a full, "out of the box" factory reset on an HP OfficeJet 6700 AIO Printer, here are the steps. 1. With the printer turned off, hold the power button for 5 seconds (you might see the indicator light on the power button blink once). Then let go. 2. Once the printer cycles on, press the "Home" button (top left, almost even with the top of the touchscreen panel and about 1 or 2 centimeters to the left of the touchscreen). Then press the "Return" button (bottom left, almost even with the bottom of the touchscreen panel and about 1 - 2 centimeters left of the touchscreen). Then press the Home button two more times. 3. You will see "Engineering Menu" pop up. Touch "Service Menu", then touch the right arrow button until you see "Resets Menu". Then, touch the right arrow button until you see "OOBE Reset". 4. You may see a grid background with a blue progress bar. Then press and hold the power button until the printer turns off. When you turn the printer back on, it will be in its "out of the box" state. This is helpful if you have a printer you need to return to the store, or if you are trying to sell one and don't want all of your information going to the new owner. Hope this helps.